

### 20 Key Basketball Remote for the 8000 Series Multi-Sport Console

#### 20 Key Remote

for the 8000 Multi-Sport Console  
Basketball



Remote Receiver

#### OVERALL DIMENSION

5" high x 2.75" wide x 7/8" deep.

#### FEATURES

Ability to control most functions while connected to the 8000 Series Multi-Sport Console (sold separately). Console can still perform other duties while remote is in use.

#### KEYS

Responsive tactile embossed keys on a durable polyester overlay. Pressing a red edit key allows remote to send numeric data and allow for quick edits of scores, time and shot clock timer.

#### Basketball:

Timer: Start and Stop the Clock and Edit the Time.

Scores: Add 2 or 1 to Home or Guest Scores or Edit via Number Keys.

Control Brightness of Scoreboard LEDs.

Sound the Horn.

Advance the Period.

Change the Bonus/Double Bonus Status.

Change Possession.

Change Timer Direction from Down to Up.

Shot Clock: Trigger 2 resets for the Shot Clock.

Blank the Shot Clock.

#### CONSTRUCTION

Remote is made from durable plastic enclosure.

Radio receiver is made from extruded aluminum to match 8000 Series Multi-Sport Console.

#### RADIO REMOTE 418 MHz

Remote requires the Remote Receiver (shown above). Receiver connects directly to the Auxiliary I/O on the 8000 Series Multi-Sport Console via supplied Ethernet Cable. Radio ID can be easily changed in the remote and learned to the Remote Receiver, making it possible to control the same receiver with multiple remotes, or to control multiple receivers with multiple remotes.

#### POWER REQUIREMENTS

Remote requires two (2) AA Batteries (included). Receiver gets power from the 8000 Series Multi-Sport Console, which runs on rechargeable batteries.

#### WEIGHT

2.9 oz. (4.9 oz. with Batteries).

#### WARRANTY

Five year guarantee against defects in materials and workmanship. Factory repair service for parts in warranty. Union label.